



INOPLACER Smart-Feeder



SmartFeeder
8mm/2




SmartFeeder
8mm/2



SmartFeeder
8mm/4



SmartFeeder
12mm



SmartFeeder
16mm



SmartFeeder
24mm



SmartFeeder
32mm



SmartFeeder
44mm



SmartFeeder
56mm

	Feeder 8 × 2 mm für 0201	Feeder 8 × 2 mm für 0402	Feeder 8 × 4 mm	Feeder 12 mm	Feeder 16 mm
Bandbreite:	8mm	8mm	8mm	12 mm	16 mm
Schrittweite:	2 mm	2 mm	4mm	4mm	4 / 8 / 12 / 16 mm
Schlitztiefe:	2,5 mm	2,5 mm	2,5 mm	2,5 mm	11 mm
Griff:	grün	blau	schwarz	schwarz	schwarz
Komponente:	0201	0402	0603, 0805, 1206, IC		

	Feeder 24 mm	Feeder 32 mm	Feeder 44 mm	Feeder 56 mm	Feeder 72 mm
Bandbreite:	24 mm	32 mm	44 mm	56 mm	72 mm
Schrittweite:	4 / 8 / 12 / 16 / 20 / 24 mm	4 / 8 / 12 / 16 / 20 / 24 / 32 mm	4 / 8 / 12 / 16 / 20 / 24 / 32 / 36 mm	4 / 8 / 12 / 16 / 20 / 24 / 32 / 36 mm	4 / 8 / 12 / 16 / 20 / 24 / 32 / 36 mm
Schlitztiefe:	15 mm	15 mm	15 mm	15 mm	15 mm
Griff:	schwarz	schwarz	schwarz	schwarz	schwarz